

1	2	3	4	5	6																																
TFT LCD ER-TFTM019-1-SPI to Raspberry pi (4-Wire SPI Interface)																																					
D	<div><div>4-wire SPI Interface</div><table><tr><td>GND</td><td>1</td><td>Power grond</td><td>GND(Physical PIN6)</td></tr><tr><td>VCC</td><td>2</td><td>Power 3.3V</td><td>3.3V(Physical PIN1)</td></tr><tr><td>SCL</td><td>3</td><td>Serial clock</td><td>SCLK(Physical PIN23)</td></tr><tr><td>SDA</td><td>4</td><td>Serial Data input</td><td>MOSI(Physical PIN19)</td></tr><tr><td>RES</td><td>5</td><td>Reset input</td><td>GPIO0.6(Physical PIN22) (bcm2835 25)</td></tr><tr><td>DC</td><td>6</td><td>Data/Command</td><td>GPIO0.5(Physical PIN18) (bcm2835 24)</td></tr><tr><td>CS</td><td>7</td><td>Chip Select</td><td>CE0(Physical PIN24) (bcm2835 8)</td></tr><tr><td>BL</td><td>8</td><td>NC</td><td></td></tr></table><div>ER-TFTM019-1Raspberry pi</div></div>				GND	1	Power grond	GND(Physical PIN6)	VCC	2	Power 3.3V	3.3V(Physical PIN1)	SCL	3	Serial clock	SCLK(Physical PIN23)	SDA	4	Serial Data input	MOSI(Physical PIN19)	RES	5	Reset input	GPIO0.6(Physical PIN22) (bcm2835 25)	DC	6	Data/Command	GPIO0.5(Physical PIN18) (bcm2835 24)	CS	7	Chip Select	CE0(Physical PIN24) (bcm2835 8)	BL	8	NC		D
GND	1	Power grond	GND(Physical PIN6)																																		
VCC	2	Power 3.3V	3.3V(Physical PIN1)																																		
SCL	3	Serial clock	SCLK(Physical PIN23)																																		
SDA	4	Serial Data input	MOSI(Physical PIN19)																																		
RES	5	Reset input	GPIO0.6(Physical PIN22) (bcm2835 25)																																		
DC	6	Data/Command	GPIO0.5(Physical PIN18) (bcm2835 24)																																		
CS	7	Chip Select	CE0(Physical PIN24) (bcm2835 8)																																		
BL	8	NC																																			
C	<p>== How to use ==</p> <p>1, Install the C libraries of bcm2835, see: http://www.airspayce.com/mikem/bcm2835/</p> <p>2, Change the current directory to where the Makefile and oled.c file located.</p> <p>3, Clean the file with: make clean</p> <p>4, Compile the file with: make</p> <p>5, Run the demo with: sudo ./tft</p>				C																																
B	<table><tr><td>REV.</td><td>DESCRIPTION OF MODIFY</td><td>MODIFY BY</td><td>DATE</td></tr><tr><td>A0</td><td>1'ST DESIGN</td><td>JIM</td><td>04-Jan-2022</td></tr><tr><td>A1</td><td></td><td></td><td></td></tr></table>				REV.	DESCRIPTION OF MODIFY	MODIFY BY	DATE	A0	1'ST DESIGN	JIM	04-Jan-2022	A1				B																				
REV.	DESCRIPTION OF MODIFY	MODIFY BY	DATE																																		
A0	1'ST DESIGN	JIM	04-Jan-2022																																		
A1																																					
A	<table><tr><td colspan="4">TitleEASTRISING TECHNOLOGY CO.,LTD. www.buydisplay.com</td></tr><tr><td>SizeA</td><td colspan="2">NumberER-TFTM019-1 (4-Wire SPI Interface)</td><td>RevisionA0</td></tr><tr><td colspan="2">Date:04-Jan-2022</td><td colspan="2">Sheet of1</td></tr><tr><td colspan="2">File</td><td colspan="2">Drawn ByJaven</td></tr></table>				TitleEASTRISING TECHNOLOGY CO.,LTD. www.buydisplay.com				SizeA	NumberER-TFTM019-1 (4-Wire SPI Interface)		RevisionA0	Date:04-Jan-2022		Sheet of1		File		Drawn ByJaven		A																
TitleEASTRISING TECHNOLOGY CO.,LTD. www.buydisplay.com																																					
SizeA	NumberER-TFTM019-1 (4-Wire SPI Interface)		RevisionA0																																		
Date:04-Jan-2022		Sheet of1																																			
File		Drawn ByJaven																																			
1	2	3	4	5	6																																